

Babystep8

From OSDev Wiki

32-bit printing

Here is the same non-BIOS screen print AsmExample as before, but adjusted to use 32-bit registers and offsets. The 'complex' string instructions have been replaced.

```
;-----
dochar:
    call cprint
sprint:
    mov eax, [esi]
    lea esi, [esi+1]
    cmp al, 0
    jne dochar
    add byte [ypos], 1
    mov byte [xpos], 0
    ret

cprint:
    mov ah, 0x0F
    mov ecx, eax
    movzx eax, byte [ypos]
    mov edx, 160
    mul edx
    movzx ebx, byte [xpos]
    shl ebx, 1

    mov edi, 0xb8000
    add edi, eax
    add edi, ebx

    mov eax, ecx
    mov word [ds:edi], ax
    add byte [xpos], 1

    ret

;-----

printreg32:
```

Babystep8

Tutorial

Previous

Babystep7

Next

```
    mov edi, outstr32
    mov eax, [reg32]
    mov esi, hexstr
    mov ecx, 8
```

```
hexloop:
```

```
    rol eax, 4
    mov ebx, eax
    and ebx, 0x0f ;
    mov bl, [esi + ebx]
    mov [edi], bl
    inc edi
    dec ecx
    jnz hexloop
```

```
    mov esi, outstr32
    call sprint
```

```
    ret
```

```
;-----
```

```
xpos db 0
ypos db 0
hexstr db '0123456789ABCDI
outstr32 db '00000000', 0
reg32 dd 0
```

```
;-----
```



Retrieved from "<http://wiki.osdev.org/index.php?title=Babystep8&oldid=7946>"

Category: Babystep

- This page was last modified on 13 May 2009, at 07:27.
- This page has been accessed 34,300 times.